

Secura Key
A Division of SOUL SECURITY, Inc.

28SA



| Mfg # | EZ # |
|-------|--------|
| 28SA | 029627 |

Touch Card® Access Control

- Touch Card® Stand Alone access control unit for single or multi-door applications.
- Can be programmed with programming cards for basic information or by using a PC terminal program on a laptop for more advanced features.
- Transaction information is stored by the unit and may be downloaded to a PC or serial printer.
- Up to 128, 28SA-Plus units can be connected together in a single twisted pair RS-485 network using the included RS-485 cable and the optional SK-NET™ Software for Windows® XP/Vista.
- 3 Programmable inputs for Door Monitor, Tamper Monitor, Remote Inactive, Remote Open, Arming Circuit, Bell, or User Definition.
- 65,500 Card Capacity
- 5,000 Stored Transactions
- 15 Time Zones / 32 Holidays
- TCP/IP Capability for LAN Connection
- Weather Resistant for Outdoor Installation
- True IN/OUT or Timed Antipassback
- Barium Ferrite Cards are available by special order. Please specify site code.

Radio Key® Stand Alone Access Control

- The Radio Key™ family are fully programmable, stand-alone access control system
- Proximity key tag RKKT01 for up to 600 users.
- Programming is accomplished using the keypad (RK600 & RK600T) or by using the optional programming deck RK PD1 on the RK600E.
- RK600T & RK600T allow for proximity and keypad (PIN) entry.
- Void/valid capability for up to 600 proximity key tags.
- Up to 6" reading distance.
- Connect a PC or Serial Printer with optional Audit Trail Module RKAT.
- Power Requirements: 9-14 VDC, 50 mA average, 150 mA maximum. Use optional RK600PS power supply
- Outputs: Latch and alarm shunt. DPDT contact, 0.5A max. @250 VAC; 2A max. @24 VAC or DC
- Input: Request to exit.
- Either unit can add the optional RKAR unit that allows for back to back access or for an additional secure reader in exterior locations.
- Temperature Range: -40° to +70°C
- Stores the last 150 transactions



RKAR

RK600
RK600T



RK600

RK600E



RK PD1



RKAT

- Program unit with PC.
- Upload History to PC for display/printout.
- Upload key tag or PIN status to PC.
- Copy key tag or PIN status from one RK600 to others using a PC.
- RS-232 Interface with DB9 connector.
- Print key tag or PIN Status Report.

| Mfg # | Description | EZ # |
|-----------|---------------------------------------|--------|
| RK600 | Reader | 065263 |
| RK600T | Reader with 10 Proximity Tags | 066745 |
| RK600E | Reader | 072915 |
| RKPD1 | Program Deck for RK600E | 072916 |
| RK600PS | Power Supply | 067974 |
| RKAR | Auxillary Reader | 065264 |
| RKAT | Audit Trail And Communications Module | 066744 |
| RKKT01 10 | Proximity Tags (Pkg of 10) | 065265 |